863-875 MHz Band Pass Filter SRFS-BPF-869MN1

Specifications

1	Center Frequency(F0)	869MHz	
2	Pass Band Frequency	863 ~ 875MHz	
3	Pass Band Insertion Loss	≤3.5dB	
5	Pass Band VSWR	≤1.3	
6	Stop Band Rejection	≥40dB @ DC ~ 860MHz	≥40dB @ 878 ~ 3000MHz
7	Impedance	50 Ohms	
8	Power Handling	20W max	
9	Connectors	N Female	
10	Surface Finish	Black Painted	
11	Temperature Range	-20℃ ~ +60℃	
12	Weight	About 700g	

Dimensions(mm)

