916-924 MHz Band Pass Filter SRFS-BPF-920MS1

Specifications

1	Center Frequency(F0)	920 MHz	
2	Pass Band Frequency	916 ~ 924 MHz	
3	Pass Band Insertion Loss	≤2.5dB	
4	Pass Band Ripple	≤0.5dB	
5	Pass Band VSWR	≤1.15	
6	Stop Band Rejection	≥60dB @ DC ~ 890MHz	≥60dB @ 950 ~ 2500MHz
7	Impedance	50 Ohms	
8	Power Handling	20W max	
9	Connectors	SMA Female	
10	Surface Finish	Black Painted	
11	Temperature Range	-10℃ ~ +50℃	
12	Weight	155g	

Dimensions(mm)

